

FILTRO MCF 7894D

\$14,995.00



Poderoso filtro de cobre anti-interferencias para la Banda C, rechaza interferencias de sistemas de radar y navegación marítima.

Filtro MCF 7894D

Características:

| Specifications: | |
|--|---|
| Passband: | 3.7-4.2 GHz |
| Custom Passbands Available Upon Request | |
| Insertion Loss: | 0.4 dB Typ at Fo 0.5 dB roll off at band edge |
| VSWR: | 1.33:1 Max |
| Return Loss: | 18 dB Min |
| Group Delay Variation: | Less than 8 ns Typ |
| Rejection: | |
| 25 dB Min | 3.65/4.25 |
| 60 dB Min | 3.55/4.35 GHz |
| 70 dB Min | 3.50/4.40 GHz |
| Mechanical Specifications: | |
| Weight | 2.60 lbs |
| Dimensions | 5 3/4" L x 2 3/4" H x 3 7/8" D |
| Flanges | CPR-229G (Input) |
| | CPR-229F (Output) |

* Half gasket is supplied with each model